

# Tabletop Mixer Amplifier with USB/SD/FM/Bluetooth/Echo

## CP-120M CP-240M CP-350M CP-500M



### Feature:

- Compact mini size public address amplifier
- Tabletop mixer amplifier with Mp3 player, FM radio & bluetooth
- Rate power output at 120W, 240W, 350W, 500W
- Speaker output of 100V & 4-8 Ohm
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and bluetooth
- LED indicators for power, clip, protect and signal
- Mic1 of 6.3mm Jack input on front panel
- Mic/line2 switchable input balanced XLR with +48V phantom power
- Line1 input of RCA input and one RCA line output
- With mute and EMC input from fire alarm system
- Input priority from high to low: MUTE, EMC and others inputs
- With Echo features and volume control
- Volume control for Mic1, Echo, line 1, Mic2/line2, bass/treble and master
- Complete amplifier protection includes short-circuit, clip, overload and high temp
- 110V-230V AC & 24V DC both power supply system

### Specification:

Model	CP-120M	CP-240M	CP-350M	CP-500M
Description	Mini Mixer Amplifier with USB/SD/FM/Bluetooth/Echo			
Rated Power Output	120W	240W	350W	500W
Speaker Outputs	100V & 4-8 Ohm			
Connector	Mic1 of 6.3mm Jack on front panel Mic/line2 switchable input balanced XLR with +48V phantom power Line1 input of RCA input and one RCA line output With mute and EMC input from fire alarm system			
Input	MIC: 5-8mV, 600Ω; Line, 150-470mV, 10KΩ, unbalanced RCA			
Line Out	0.775(0dBV)			
Frequency Response	60Hz-20kHz(±3dB)			
S/N Ratio	Line ≥ 85dB, Mic≥ 72dB			
THD	Less than 0.5%			
Protection	Short-circuit, clip, overload and high temp protection			
Power Consumption	200W	400W	500W	650W
Power Supply	110V-230V AC & 24V DC; 50-60Hz			
Dimension	320×210×90 mm			
Weight	3.4kg	3.5kg	3.6kg	3.7kg

### Rear Panel:

