

Mini Mixer Amplifier with USB/SD/FM/Bluetooth/Echo CP-30M CP-60M



Feature:

- Compact mini size public address amplifier
- Tabletop mixer amplifier with Mp3 player, FM radio & bluetooth
- Rate power output at 30W & 60W
- Speaker output of 100V or 70V & 4-8 Ohm
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and bluetooth
- LED indicators for power, clip, protect and signal
- Mic1 of 6.3mm Jack input on front panel
- Mic/line2 switchable input balanced XLR with +48V phantom power
- Line1 input of RCA input and one RCA line output
- With mute and EMC input from fire alarm system
- Input priority from high to low: MUTE, EMC and others inputs
- With Echo features and volume control
- Volume control for Mic1, Echo, line 1, Mic2/line2, bass/treble and master
- Complete amplifier protection includes short-circuit, clip, overload and high temp
- 230V AC & 12V DC both power supply system

Specification:

Model	CP-30M	CP-60M
Description	Mini Mixer Amplifier with USB/SD/FM/Bluetooth/Echo	
Rated Power Output	30W	60W
Speaker Outputs	100V or 70V & 4-8 Ohm	
Connector	Mic1 of 6.3mm Jack on front panel Mic/line2 switchable input balanced XLR with +48V phantom power Line1 input of RCA input and one RCA line output With mute and EMC input from fire alarm system	
Input	MIC: 5-8mV, 600Ω; Line, 150-470mV, 10KΩ, unbalanced RCA	
Line Out	0.775(0dBV)	
Frequency Response	60Hz-15kHz(±3dB)	
S/N Ratio	Line ≥ 85dB, Mic ≥ 72dB	
THD	Less than 0.5%	
Protection	Short-circuit, clip, overload and high temp protection	
Power Consumption	40W	80W
Power Supply	230V AC & 12V DC; 50-60Hz	
Dimension	220×200×72mm	
Weight	2.5kg	2.6kg

Rear Panel:

